



VGPNRRKIT

Technical Product Data

Features

- **Re-Radiating Amplifier with Power Supply**
Excellent Gain Flatness
- **Optional Mounting Kit Hardware**
Re-Radiating Amp Mount
- **Variable Gain**
Re-Radiating Amp Gain Varies from -3 to +23 dB

Description

The GPS Variable Gain Portable Re-Radiating Kit (VGPNRRKIT) is a re-radiating system that allows re-radiation of the GPS L1 signal indoors. The VGPNRRKIT consists of a re-radiating amplifier with a variable gain pot range control that allows for easy gain adjustment from -3dB to 23dB, a wall mount plug-in transformer that powers the entire system, and an L1 passive re-radiating antenna. The GPS L1 signal from the roof antenna is amplified, adjusted appropriately and radiated indoors. Thus, if a receiver has line of sight with the re-radiating antenna, it can receive the GPS signal indoors up to 100 feet away.

Re-Radiating Amplifier

Electrical Specifications, $T_A = 25^{\circ}\text{C}$

Parameter	Conditions	Min	Typ	Max	Units
Freq. Range	Ant - J1	1.1		1.7	GHz
In/Out Imped.	Ant, J1		50		Ω
Gain ⁽¹⁾					
	Variable Gain Option	-3		23	dB
Input SWR ⁽²⁾	J1 - 50 Ω			1.8:1	-
Output SWR	Ant - 50 Ω			1.8:1	-
Noise Figure	Ant - J1		3.3	3.5	dB
Gain Flatness	L1 - L2 ; Ant - J1		0.5	1	dB
Reverse Isolation	J1 - Ant	35			dB
Group delay Flatness	$\tau_{d,max} - \tau_{d,min}$; Ant - J1			1	ns

(1) See LA20RPDC Data Sheet for performance plots

Re-Radiating Antenna

Electrical Specifications, $T_A = 25^{\circ}\text{C}$

Parameter	Conditions	Min	Typ	Max	Units
Frequency	L1		1.575		GHz
Bandwidth				20	MHz
Impedance			50		Ω
Peak Gain			3		dBic
Output SWR				1.5:1	-
Polarization			RHCP		-

Available Options

Re-Radiating Amp System Power Supply Options		
Source Voltage Options	VOLTAGE INPUT	STYLE
	110VAC	Transformer (Wall Mount)
	220 VAC	Transformer (Wall Mount)
	240 VAC (United Kingdom)	Transformer (Wall Mount)
	Customer Supplied DC 9-32 VDC	Military Style Connector
Re-Radiating Amp Gain Control Options		
Normal Gain	Gain ≥ 20 dB	
Variable Gain	-3 \leq Gain \leq 23dB	
Re-Radiating Amp RF Connector Options		
Connector Options	CONNECTOR STYLE	CHARGE
	Type N	NC
	Type SMA	NC
	Type TNC	NC
	Type BNC	NC

Part Number

VG PNRRKIT - S / 110

Gain Option:

VG = Variable Gain; **Blank** = Normal

Connector Options:

N = N type; **S** = SMA; **T** = TNC; **B** = BNC

Source Voltage:

110 - Transformer, **220** - Transformer, **240** - U.K. Transformer **MC** - Military Conn. (User supplies DC Voltage)